

Click Here to Watch Video On YouTube More Important Solved Question

TABLE OF INFORMATION FOR 2002

CONSTANTS AND CONVERSION FACTORS		UNITS		PREFIXES																																		
		Name	Symbol	Factor	Prefix	Symbol																																
1 unified atomic mass unit,	$1 \text{ u} = 1.66 \times 10^{-27} \text{ kg}$ $= 931 \text{ MeV}/c^2$	meter	m	10^9	giga	G																																
Proton mass,	$m_p = 1.67 \times 10^{-27} \text{ kg}$	kilogram	kg	10^6	mega	M																																
Neutron mass,	$m_n = 1.67 \times 10^{-27} \text{ kg}$	second	s	10^3	kilo	k																																
Electron mass,	$m_e = 9.11 \times 10^{-31} \text{ kg}$	ampere	A	10^{-2}	centi	c																																
Magnitude of the electron charge,	$e = 1.60 \times 10^{-19} \text{ C}$	kelvin	K	10^{-3}	milli	m																																
Avogadro's number,	$N_0 = 6.02 \times 10^{23} \text{ mol}^{-1}$	mole	mol	10^{-6}	micro	μ																																
Universal gas constant,	$R = 8.31 \text{ J}/(\text{mol} \cdot \text{K})$	hertz	Hz	10^{-9}	nano	n																																
Boltzmann's constant,	$k_B = 1.38 \times 10^{-23} \text{ J/K}$	newton	N	10^{-12}	pico	p																																
Speed of light,	$c = 3.00 \times 10^8 \text{ m/s}$	pascal	Pa	VALUES OF TRIGONOMETRIC FUNCTIONS FOR COMMON ANGLES <table border="1" style="margin: auto; border-collapse: collapse;"> <thead> <tr> <th>θ</th> <th>$\sin \theta$</th> <th>$\cos \theta$</th> <th>$\tan \theta$</th> </tr> </thead> <tbody> <tr> <td>0°</td> <td>0</td> <td>1</td> <td>0</td> </tr> <tr> <td>30°</td> <td>1/2</td> <td>$\sqrt{3}/2$</td> <td>$\sqrt{3}/3$</td> </tr> <tr> <td>37°</td> <td>3/5</td> <td>4/5</td> <td>3/4</td> </tr> <tr> <td>45°</td> <td>$\sqrt{2}/2$</td> <td>$\sqrt{2}/2$</td> <td>1</td> </tr> <tr> <td>53°</td> <td>4/5</td> <td>3/5</td> <td>4/3</td> </tr> <tr> <td>60°</td> <td>$\sqrt{3}/2$</td> <td>1/2</td> <td>$\sqrt{3}$</td> </tr> <tr> <td>90°</td> <td>1</td> <td>0</td> <td>∞</td> </tr> </tbody> </table>			θ	$\sin \theta$	$\cos \theta$	$\tan \theta$	0°	0	1	0	30°	1/2	$\sqrt{3}/2$	$\sqrt{3}/3$	37°	3/5	4/5	3/4	45°	$\sqrt{2}/2$	$\sqrt{2}/2$	1	53°	4/5	3/5	4/3	60°	$\sqrt{3}/2$	1/2	$\sqrt{3}$	90°	1	0	∞
θ	$\sin \theta$	$\cos \theta$	$\tan \theta$																																			
0°	0	1	0																																			
30°	1/2	$\sqrt{3}/2$	$\sqrt{3}/3$																																			
37°	3/5	4/5	3/4																																			
45°	$\sqrt{2}/2$	$\sqrt{2}/2$	1																																			
53°	4/5	3/5	4/3																																			
60°	$\sqrt{3}/2$	1/2	$\sqrt{3}$																																			
90°	1	0	∞																																			
Planck's constant,	$h = 6.63 \times 10^{-34} \text{ J} \cdot \text{s}$ $= 4.14 \times 10^{-15} \text{ eV} \cdot \text{s}$	joule	J																																			
	$hc = 1.99 \times 10^{-25} \text{ J} \cdot \text{m}$ $= 1.24 \times 10^3 \text{ eV} \cdot \text{nm}$	watt	W																																			
Vacuum permittivity,	$\epsilon_0 = 8.85 \times 10^{-12} \text{ C}^2/\text{N} \cdot \text{m}^2$	coulomb	C																																			
Coulomb's law constant,	$k = 1/4\pi\epsilon_0 = 9.0 \times 10^9 \text{ N} \cdot \text{m}^2/\text{C}^2$	volt	V																																			
Vacuum permeability,	$\mu_0 = 4\pi \times 10^{-7} (\text{T} \cdot \text{m})/\text{A}$	ohm	Ω																																			
Magnetic constant,	$k' = \mu_0/4\pi = 10^{-7} (\text{T} \cdot \text{m})/\text{A}$	henry	H																																			
Universal gravitational constant,	$G = 6.67 \times 10^{-11} \text{ m}^3/\text{kg} \cdot \text{s}^2$	farad	F																																			
Acceleration due to gravity at the Earth's surface,	$g = 9.8 \text{ m/s}^2$	tesla	T																																			
1 atmosphere pressure,	$1 \text{ atm} = 1.0 \times 10^5 \text{ N/m}^2$ $= 1.0 \times 10^5 \text{ Pa}$	degree Celsius	$^\circ\text{C}$																																			
1 electron volt,	$1 \text{ eV} = 1.60 \times 10^{-19} \text{ J}$	electron-volt	eV																																			

The following conventions are used in this examination.

- I. Unless otherwise stated, the frame of reference of any problem is assumed to be inertial.
- II. The direction of any electric current is the direction of flow of positive charge (conventional current).
- III. For any isolated electric charge, the electric potential is defined as zero at an infinite distance from the charge.
- *IV. For mechanics and thermodynamics equations, W represents the work done on a system.

*Not on the Table of Information for Physics C, since Thermodynamics is not a Physics C topic.

Provided by MS Rehman

YouTube : MS CreaTive PlatForm

ADVANCED PLACEMENT PHYSICS B EQUATIONS FOR 2002

NEWTONIAN MECHANICS

$$v = v_0 + at$$

$$x = x_0 + v_0 t + \frac{1}{2} at^2$$

$$v^2 = v_0^2 + 2a(x - x_0)$$

$$\Sigma \mathbf{F} = \mathbf{F}_{net} = m\mathbf{a}$$

$$F_{fric} \leq \mu N$$

$$a_c = \frac{v^2}{r}$$

$$\tau = rF \sin \theta$$

$$\mathbf{p} = m\mathbf{v}$$

$$\mathbf{J} = \mathbf{F}\Delta t = \Delta \mathbf{p}$$

$$K = \frac{1}{2} mv^2$$

$$\Delta U_g = mgh$$

$$W = \mathbf{F} \cdot \Delta \mathbf{r} = F\Delta r \cos \theta$$

$$P_{avg} = \frac{W}{\Delta t}$$

$$P = \mathbf{F} \cdot \mathbf{v} = Fv \cos \theta$$

$$\mathbf{F}_s = -k\mathbf{x}$$

$$U_s = \frac{1}{2} kx^2$$

$$T_s = 2\pi\sqrt{\frac{m}{k}}$$

$$T_p = 2\pi\sqrt{\frac{\ell}{g}}$$

$$T = \frac{1}{f}$$

$$F_G = -\frac{Gm_1m_2}{r^2}$$

$$U_G = -\frac{Gm_1m_2}{r}$$

a = acceleration
 F = force
 f = frequency
 h = height
 J = impulse
 K = kinetic energy
 k = spring constant
 ℓ = length
 m = mass
 N = normal force
 P = power
 p = momentum
 r = radius or distance
 \mathbf{r} = position vector
 T = period
 t = time
 U = potential energy
 v = velocity or speed
 W = work done on a system
 x = position
 μ = coefficient of friction
 θ = angle
 τ = torque

ELECTRICITY AND MAGNETISM

$$F = \frac{1}{4\pi\epsilon_0} \frac{q_1q_2}{r^2}$$

$$\mathbf{E} = \frac{\mathbf{F}}{q}$$

$$U_E = qV = \frac{1}{4\pi\epsilon_0} \frac{q_1q_2}{r}$$

$$E_{avg} = -\frac{V}{d}$$

$$V = \frac{1}{4\pi\epsilon_0} \sum_i \frac{q_i}{r_i}$$

$$C = \frac{Q}{V}$$

$$C = \frac{\epsilon_0 A}{d}$$

$$U_c = \frac{1}{2} QV = \frac{1}{2} CV^2$$

$$I_{avg} = \frac{\Delta Q}{\Delta t}$$

$$R = \frac{\rho\ell}{A}$$

$$V = IR$$

$$P = IV$$

$$C_p = \sum_i C_i$$

$$\frac{1}{C_s} = \sum_i \frac{1}{C_i}$$

$$R_s = \sum_i R_i$$

$$\frac{1}{R_p} = \sum_i \frac{1}{R_i}$$

$$F_B = qvB \sin \theta$$

$$F_B = BI\ell \sin \theta$$

$$B = \frac{\mu_0 I}{2\pi r}$$

$$\phi_m = \mathbf{B} \cdot \mathbf{A} = BA \cos \theta$$

$$\mathcal{E}_{avg} = -\frac{\Delta\phi_m}{\Delta t}$$

$$\mathcal{E} = B\ell v$$

A = area
 B = magnetic field
 C = capacitance
 d = distance
 E = electric field
 \mathcal{E} = emf
 F = force
 I = current
 ℓ = length
 P = power
 Q = charge
 q = point charge
 R = resistance
 r = distance
 t = time
 U = potential (stored) energy
 V = electric potential or potential difference
 v = velocity or speed
 ρ = resistivity
 ϕ_m = magnetic flux

ADVANCED PLACEMENT PHYSICS B EQUATIONS FOR 2002

FLUID MECHANICS AND THERMAL PHYSICS

$$p = p_0 + \rho gh$$

$$F_{buoy} = \rho Vg$$

$$A_1 v_1 = A_2 v_2$$

$$p + \rho gy + \frac{1}{2} \rho v^2 = \text{const.}$$

$$\Delta \ell = \alpha \ell_0 \Delta T$$

$$Q = mL$$

$$Q = mc\Delta T$$

$$p = \frac{F}{A}$$

$$pV = nRT$$

$$K_{avg} = \frac{3}{2} k_B T$$

$$v_{rms} = \sqrt{\frac{3RT}{M}} = \sqrt{\frac{3k_B T}{\mu}}$$

$$W = -p\Delta V$$

$$Q = nc\Delta T$$

$$\Delta U = Q + W$$

$$\Delta U = nc_V \Delta T$$

$$e = \left| \frac{W}{Q_H} \right|$$

$$e_c = \frac{T_H - T_C}{T_H}$$

A = area

c = specific heat or molar specific heat

e = efficiency

F = force

h = depth

K_{avg} = average molecular kinetic energy

L = heat of transformation

ℓ = length

M = molecular mass

m = mass of sample

n = number of moles

p = pressure

Q = heat transferred to a system

T = temperature

U = internal energy

V = volume

v = velocity or speed

v_{rms} = root-mean-square velocity

W = work done on a system

y = height

α = coefficient of linear expansion

μ = mass of molecule

ρ = density

WAVES AND OPTICS

$$v = f\lambda$$

$$n = \frac{c}{v}$$

$$n_1 \sin \theta_1 = n_2 \sin \theta_2$$

$$\sin \theta_c = \frac{n_2}{n_1}$$

$$\frac{1}{s_i} + \frac{1}{s_o} = \frac{1}{f}$$

$$M = \frac{h_i}{h_o} = -\frac{s_i}{s_o}$$

$$f = \frac{R}{2}$$

$$d \sin \theta = m\lambda$$

$$x_m \approx \frac{m\lambda L}{d}$$

d = separation

f = frequency or focal length

h = height

L = distance

M = magnification

m = an integer

n = index of refraction

R = radius of curvature

s = distance

v = speed

x = position

λ = wavelength

θ = angle

ATOMIC AND NUCLEAR PHYSICS

$$E = hf = pc$$

$$K_{max} = hf - \phi$$

$$\lambda = \frac{h}{p}$$

$$\Delta E = (\Delta m)c^2$$

E = energy

f = frequency

K = kinetic energy

m = mass

p = momentum

λ = wavelength

ϕ = work function

GEOMETRY AND TRIGONOMETRY

Rectangle

$$A = bh$$

Triangle

$$A = \frac{1}{2}bh$$

Circle

$$A = \pi r^2$$

$$C = 2\pi r$$

Parallelepiped

$$V = \ell wh$$

Cylinder

$$V = \pi r^2 \ell$$

$$S = 2\pi r \ell + 2\pi r^2$$

Sphere

$$V = \frac{4}{3}\pi r^3$$

$$S = 4\pi r^2$$


Right Triangle

$$a^2 + b^2 = c^2$$

$$\sin \theta = \frac{a}{c}$$

$$\cos \theta = \frac{b}{c}$$

$$\tan \theta = \frac{a}{b}$$



ADVANCED PLACEMENT PHYSICS C EQUATIONS FOR 2002

MECHANICS

$v = v_0 + at$	$a =$ acceleration
$x = x_0 + v_0t + \frac{1}{2}at^2$	$F =$ force
$v^2 = v_0^2 + 2a(x - x_0)$	$f =$ frequency
$\sum \mathbf{F} = \mathbf{F}_{net} = m\mathbf{a}$	$h =$ height
$\mathbf{F} = \frac{d\mathbf{p}}{dt}$	$I =$ rotational inertia
$\mathbf{J} = \int \mathbf{F} dt = \Delta\mathbf{p}$	$J =$ impulse
$\mathbf{p} = m\mathbf{v}$	$K =$ kinetic energy
$F_{fric} \leq \mu N$	$k =$ spring constant
$W = \int \mathbf{F} \cdot d\mathbf{r}$	$\ell =$ length
$K = \frac{1}{2}mv^2$	$L =$ angular momentum
$P = \frac{dW}{dt}$	$m =$ mass
$P = \mathbf{F} \cdot \mathbf{v}$	$N =$ normal force
$\Delta U_g = mgh$	$P =$ power
$a_c = \frac{v^2}{r} = \omega^2 r$	$p =$ momentum
$\boldsymbol{\tau} = \mathbf{r} \times \mathbf{F}$	$r =$ radius or distance
$\sum \boldsymbol{\tau} = \boldsymbol{\tau}_{net} = I\boldsymbol{\alpha}$	$\mathbf{r} =$ position vector
$I = \int r^2 dm = \sum mr^2$	$T =$ period
$\mathbf{r}_{cm} = \frac{\sum m\mathbf{r}}{\sum m}$	$t =$ time
$v = r\omega$	$U =$ potential energy
$\mathbf{L} = \mathbf{r} \times \mathbf{p} = I\boldsymbol{\omega}$	$v =$ velocity or speed
$K = \frac{1}{2}I\omega^2$	$W =$ work done on a system
$\omega = \omega_0 + \alpha t$	$x =$ position
$\theta = \theta_0 + \omega_0 t + \frac{1}{2}\alpha t^2$	$\mu =$ coefficient of friction
$\mathbf{F}_s = -k\mathbf{x}$	$\theta =$ angle
$U_s = \frac{1}{2}kx^2$	$\tau =$ torque
$T = \frac{2\pi}{\omega} = \frac{1}{f}$	$\omega =$ angular speed
$T_s = 2\pi\sqrt{\frac{m}{k}}$	$\alpha =$ angular acceleration
$T_p = 2\pi\sqrt{\frac{\ell}{g}}$	
$\mathbf{F}_G = -\frac{Gm_1m_2}{r^2}\hat{\mathbf{r}}$	
$U_G = -\frac{Gm_1m_2}{r}$	


ELECTRICITY AND MAGNETISM

$F = \frac{1}{4\pi\epsilon_0} \frac{q_1q_2}{r^2}$	$A =$ area
$\mathbf{E} = \frac{\mathbf{F}}{q}$	$B =$ magnetic field
$\oint \mathbf{E} \cdot d\mathbf{A} = \frac{Q}{\epsilon_0}$	$C =$ capacitance
$E = -\frac{dV}{dr}$	$d =$ distance
$V = \frac{1}{4\pi\epsilon_0} \sum_i \frac{q_i}{r_i}$	$E =$ electric field
$U_E = qV = \frac{1}{4\pi\epsilon_0} \frac{q_1q_2}{r}$	$\mathcal{E} =$ emf
$C = \frac{Q}{V}$	$F =$ force
$C = \frac{\kappa\epsilon_0 A}{d}$	$I =$ current
$C_p = \sum_i C_i$	$L =$ inductance
$\frac{1}{C_s} = \sum_i \frac{1}{C_i}$	$\ell =$ length
$I = \frac{dQ}{dt}$	$n =$ number of loops of wire per unit length
$U_c = \frac{1}{2}QV = \frac{1}{2}CV^2$	$P =$ power
$R = \frac{\rho\ell}{A}$	$Q =$ charge
$V = IR$	$q =$ point charge
$R_s = \sum_i R_i$	$R =$ resistance
$\frac{1}{R_p} = \sum_i \frac{1}{R_i}$	$r =$ distance
$P = IV$	$t =$ time
$\mathbf{F}_M = q\mathbf{v} \times \mathbf{B}$	$U =$ potential or stored energy
$\oint \mathbf{B} \cdot d\boldsymbol{\ell} = \mu_0 I$	$V =$ electric potential
$\mathbf{F} = \int I d\boldsymbol{\ell} \times \mathbf{B}$	$v =$ velocity or speed
$B_s = \mu_0 nI$	$\rho =$ resistivity
$\phi_m = \int \mathbf{B} \cdot d\mathbf{A}$	$\phi_m =$ magnetic flux
$\mathcal{E} = -\frac{d\phi_m}{dt}$	$\kappa =$ dielectric constant
$\mathcal{E} = -L\frac{dI}{dt}$	
$U_L = \frac{1}{2}LI^2$	

GEOMETRY AND TRIGONOMETRY

- | | | |
|----------------|---------------------|----------------------------|
| Rectangle | $A = bh$ | $A = \text{area}$ |
| Triangle | $A = \frac{1}{2}bh$ | $C = \text{circumference}$ |
| Circle | $A = \pi r^2$ | $V = \text{volume}$ |
| Parallelepiped | $V = \ell wh$ | $S = \text{surface area}$ |
| Cylinder | $V = \pi r^2 \ell$ | $b = \text{base}$ |
| Sphere | $S = 4\pi r^2$ | $h = \text{height}$ |
| | | $\ell = \text{length}$ |
| | | $w = \text{width}$ |
| | | $r = \text{radius}$ |

- Right Triangle
- $$a^2 + b^2 = c^2$$
- $$\sin \theta = \frac{a}{c}$$
- $$\cos \theta = \frac{b}{c}$$
- $$\tan \theta = \frac{a}{b}$$



Click here

***for
Current SOLVED
PAPERS OF
ALL SUBJECTS
2022***

Click here

***for
Current SOLVED
PAPERS OF
ALL SUBJECTS
2022***

CALCULUS

- $$\frac{df}{dx} = \frac{df}{du} \frac{du}{dx}$$
- $$\frac{d}{dx}(x^n) = nx^{n-1}$$
- $$\frac{d}{dx}(e^x) = e^x$$
- $$\frac{d}{dx}(\ln x) = \frac{1}{x}$$
- $$\frac{d}{dx}(\sin x) = \cos x$$
- $$\frac{d}{dx}(\cos x) = -\sin x$$
- $$\int x^n dx = \frac{1}{n+1} x^{n+1}, n \neq -1$$
- $$\int e^x dx = e^x$$
- $$\int \frac{dx}{x} = \ln|x|$$
- $$\int \cos x dx = \sin x$$
- $$\int \sin x dx = -\cos x$$